

Contents

SPDIFRX device tree configuration

Contents

1	Article purpose	3
2	DT bindings documentation	4
3	DT configuration	5
3.1	DT configuration (STM32 level)	5
3.2	DT configuration (board level)	5
3.3	DT configuration examples	5
4	How to configure the DT using STM32CubeMX	6
5	References	7

1 Article purpose

This article explains how to configure the [SPDIFRX internal peripheral](#) when it is assigned to the **Linux® OS**. In that case, it is controlled by the [ALSA framework](#).

The configuration is performed using the [device tree](#) mechanism that provides a hardware description of the SPDIFRX peripheral, used by the [SPDFIRX linux driver](#).

If the peripheral is assigned to another execution context, refer to [How to assign an internal peripheral to a runtime context](#) article for guidelines on peripheral assignment and configuration.

2 DT bindings documentation

STM32 SPDIFRX device tree bindings [\[1\]](#) document describes all the required and optional configuration properties.

3 DT configuration

This hardware description is a combination of STM32 microprocessor [\[2\]](#) and board device tree files. See the [Device tree](#) for an explanation of the device tree file split.

STM32CubeMX can be used to generate the board device tree. Refer to [How to configure the DT using STM32CubeMX](#) for more details.

3.1 DT configuration (STM32 level)

The SPDIFRX node is declared in `stm32mp157c.dtsi`[\[2\]](#). It describes the hardware parameters such as register addresses, interrupt, clock and DMA. This set of properties may not vary for a given STM32MPU.

Warning

This device tree part is related to STM32 microprocessors. It must be kept as is, without being modified by the end-user.

3.2 DT configuration (board level)

The SPDIFRX is an audio peripheral, which can be used as a component of a soundcard through Linux[®] kernel [ALSA framework](#). This part of the device tree allows the configuration of the SPDIFRX to implement a soundcard. Refer to [soundcard configuration](#) for examples of SPDIFRX configuration on various boards.

3.3 DT configuration examples

```
&spdifrx {
    pinctrl-names = "default", "sleep";
    pinctrl-0 = <&spdifrx_pins_a>;
    pinctrl-1 = <&spdifrx_sleep_pins_a>;
    /* Use spdifrx_pins_a instead of spdifrx_sleep_pins_a configuration,
       to allow IEC958 status bits capture, when an audio stream record is
       not active. Note that sleep state has to be defined, to allow pin state
       recovery from low power modes. */

    spdifrx_port: port {
        spdifrx_endpoint: endpoint {
            remote-endpoint = <&spdif_in_endpoint>;
        };
    };
};
```

4 How to configure the DT using STM32CubeMX

The [STM32CubeMX](#) tool can be used to configure the STM32MPU device and get the corresponding [platform configuration device tree](#) files.

The STM32CubeMX may not support all the properties described in the above [DT bindings documentation](#) paragraph. If so, the tool inserts **user sections** in the generated device tree. These sections can then be edited to add some properties and they are preserved from one generation to another. Refer to [STM32CubeMX](#) user manual for further information.

5 References

- [↑ Documentation/devicetree/bindings/sound/st,stm32-spdifrx.txt](#)
- [↑ ^{2.02.1} arch/arm/boot/dts/stm32mp157c.dtsi](#)



IMPORTANT NOTICE – READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgment.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2023 STMicroelectronics – All rights reserved