



How to populate and boot a board with OP-TEE



How to populate and boot a board with OP-TEE

Stable: 31.01.2020 - 14:01 / Revision: 31.01.2020 - 13:51

Template:ArticleApprovedVersion

Contents

1 Introduction	2
2 Usage	2
2.1 Programming the built image with OP-TEE	2
2.2 Booting the built image with OP-TEE	3

1 Introduction

OP-TEE overview can be found in [OP-TEE_overview](#) wiki page.

OP-TEE is a combined feature from Open Embedded point of view.

A combined feature is a combination of 2 Yocto variables `MACHINE_FEATURES` and `DISTRO_FEATURES`.

So a combined feature is activated only after these two variables are set.

Once the machine is defined with `MACHINE_FEATURES += "optee"` and the distro is set with `DISTRO_FEATURES_append = " optee "`, building the OpenSTLinux distribution will provide all necessary binaries to populate and boot with OP-TEE feature.

As a reminder, STMicroelectronics machine configuration files are located here:

- `meta-st/meta-st-stm32mp/conf/machine/*.conf`

and STMicroelectronics distribution configuration file here:

- `meta-st/meta-st-openstlinux/conf/distro/include/openstlinux.inc`

2 Usage

2.1 Programming the built image with OP-TEE

Inside the `build-<distro>-<machine>/tmp-glibc/deploy/images/stm32mp1/flashlayout_st-image-weston` folder, one of the OP-TEE Flash layout file must be selected:

```
Flashlayout_*-optee.tsv
```

Several devices to program (microSD, eâ€¦MMC...) are available on the board.

Once the Flash layout file has been selected, the `STM32CubeProgrammer` tool can be used as usual.

For microSD card and Evaluation board, the



correct Flash layout file to use is: FlashLayout_sd
card_stm32mp157c-ev1-optee.tsv

2.2 Booting the built image with OP-TEE

During boot sequence, the OP-TEE integration trace should be displayed on the UART console log. The OP-TEE core boot stage trace should look like this:

```
I/TC: Pager is enabled. Hashes: 1184 bytes  
I/TC: OP-TEE version: openstlinux-18-06-01  
I/TC: Initialized
```

The Linux kernel boot trace should show the successful probing of the OP-TEE Linux kernel driver:

```
optee: probing for conduit method from DT.  
optee: initialized driver
```

Open Portable Trusted Execution Environment

MultimediaCard

Universal Asynchronous Receiver/Transmitter

Device Tree